

PCI-1711/1731 ^{100 kS/s, 12-bit, 16-ch S.E. inputs} Low-Cost Multi-function Card



Features

- 16 single-ended analog inputs
- 12-bit A/D converter, with up to 100kHz sampling rate
- Programmable gain for each input channel
- Automatic channel/gain scanning
- On-board 1K samples FIFO buffer
- Two 12-bit analog output channels (Only for PCI-1711)
- 16 digital inputs and 16 digital outputs
- Programmable pacer/counter

Introduction

The PCI-1711/1731 is a powerful but low-cost multifunction card for the PCI bus. The PCI-1711 goes with 2 analog output channels, while the PCI-1731 doesn't. Thus, users can differentiate between PCI-1711 and PCI-1731 according to what they really need as the best solution with no extra cost.

Plug-and-Play Function

The PCI-1711/1731 fully complies with the PCI Specification Rev 2.1. and thus is a Plug-and-Play device. During card installation, you have virtually no need to set any jumpers or DIP switches. Instead, all bus-related configurations such as base I/O address and interrupts are conveniently taken care of by the Plug-and-Play function.

Flexible Input Types and Range Settings

The PCI-1711/1731 features an automatic channel/gain scanning circuit. This circuit design controls multiplexer switching during sampling. Users can set different gain values for each channel according to their needs for corresponding range of input voltage. The gain values thus selected are stored in the SRAM. This flexible design enables multi-channel and high-speed sampling for high-performance data acquisition (up to 100 kS/s .)

On-board FIFO Memory

The PCI-1711/1731 provides an on-board FIFO (First In First Out) memory buffer, storing up to 1K A/D samplings. Users can either enable or disable the interrupt request feature of the FIFO buffer. While the interrupt request for FIFO is enabled, users can further specify whether the interrupt request will be sent whenever one sampling takes place or when the FIFO buffer is half saturated. This feature enables a continuous high-speed data transfer with more predictable performance on Windows systems.

On-board Programmable Counter

The PCI-1711/1731 is equipped with a programmable counter, which can serve as a pacer trigger for A/D conversions. The counter chip is an 82C54 or equivalent, which incorporates three 16-bit counters on a 10 MHz clock. One of the three counters is used as an event counter for input channels. The other two are cascaded into a 32-bit timer for pacer triggering.

Applications

- Process monitoring and control
- Transducer and sensor measurement
- Multi-channel DC voltage measurement

Ordering information

- PCI-1711:** 100 kS/s, 12-bit, 16-ch S.E. inputs Low-Cost Multifunction Card
- PCI-1731:** 100 kS/s, 12-bit, 16-ch S.E. inputs Low-Cost Multifunction Card w/o analog output
- PCLD-8710:** Wiring Terminal Board
- PCL-10168:** 68-pin SCSI-II cable with male connectors on both ends and special shielding for noise reduction, 1m
- ADAM-3968:** 68-pin SCSI-II Wiring Terminal Board for DIN-Rail Mounting

Specifications

Analog Input

Channels	16 Single-Ended					
Resolution	12-bit					
FIFO Size	1K samples					
Max. Sampling Rate	100 KHz					
Conversion Time	10 μ s					
Input range and Gain List	Gain	1	2	4	8	16
	Input	± 10 V	± 5 V	± 2.5 V	± 1.25 V	± 0.625 V
Drift (ppm/ $^{\circ}$ C)	Gain	1	2	4	8	16
	Zero	15	15	15	15	15
	Gain	25	25	25	30	40
Small Signal Bandwidth for PGA	Gain	1	2	4	8	16
	Bandwidth	4.0 MHz	2.0 MHz	1.5 MHz	0.65 MHz	0.35 MHz
Max. Input Overvoltage	± 15 V					
Input Protect	70 Vp-p					
Input Impedance	2 MW/5 pF					
Trigger Mode	Software, On-board Programmable Pacer or externa					
Accuracy	DC	INLE: ± 0.5 LSB				
		Monotonicity: 12 bits				
		Offset error: Adjustable to zero				
		Gain error: 0.005% FSR (Gain=1)				
	AC	SNR: 68 dB				
		ENOB: 11 bits				

Analog Output *Only for PCI-1711*

Channels	2	
Resolution	12-bit	
Output Range (Internal & External Reference)	Internal Reference	0 ~ +5 V, 0 ~ -10 V
	External Reference	0 ~ +x V@ -x V (-10 \leq x \leq 10)
Accuracy	Relative	$\pm 1/2$ LSB
	Differential Non-linearity	$\pm 1/2$ LSB
Gain Error	Adjustable to zero	
Slew Rate	11V/ μ s	
Drift	40 ppm/ $^{\circ}$ C	
Driving Capability	3 mA	
Throughput	38 kHz (min.)	
Output Impedance	0.81 Ω	
Settling Time	26 μ s (to $\pm 1/2$ LSB of FSR)	
Reference Voltage	Internal	-5 V or -10 V
	External	-10 V ~ +10 V

Digital Input / Output

Input Channels	16	
Input Voltage	Low	0.8 V max.
	High	2.0 V max.
Output Channels	16	
Output Voltage	Low	0.8 V max.@ 0.8 mA (sink)
	High	2.0 V min.@ -0.4 mA (source)

Programmable Counter / Timer

Channels	1
Resolution	16-bit
Compatibility	TTL level
Base Clock	10 MHz
Max. Input Frequency	10 MHz

General

I/O Connector Type	68-pin SCSI-II female		
Dimensions	175 mm x 100 mm (6.9" x 3.9")		
Power Consumption	typical	PCI-1711 +5 V @ 850 mA	PCI-1731 +5 V @ 700 mA
	Max.	+5 V @ 1.0 A	
Temperature	Operation	0~+60 $^{\circ}$ C(32~140 $^{\circ}$ F) (refer to IEC 68-2-1,2)	
	Storage	-20~+70 $^{\circ}$ C(-4~158 $^{\circ}$ F)	
Relative Humidity	5~95%RH non-condensing (refer to IEC 68-2-3)		

Pin Assignments

A0	68	31	A11
A2	67	33	A15
A4	66	32	A15
A8	65	31	A17
A18	64	30	A18
A10	63	29	A11
A12	62	28	A13
A14	61	27	A15
AGND	60	26	AGND
DA0 REF	59	25	DAI REF
DA0 OUT	58	24	DAI OUT
ADGND	57	23	ADGND
D10	56	22	D11
D12	55	21	D13
D4	54	20	D15
D16	53	19	D17
D18	52	18	D19
D110	51	17	D111
D112	50	16	D113
D114	49	15	D115
DGND	48	14	DGND
D00	47	13	D01
D02	46	12	D03
D04	45	11	D05
D06	44	10	D07
D08	43	9	D09
D010	42	8	D011
D012	41	7	D013
D014	40	6	D015
DGND	39	5	DGND
CNT0 CLK	38	4	PACER OUT
CNT0 OUT	37	3	TRG GATE
CNT0 GATE	36	2	EXT TRG
+12V	35	1	+5V